

Product datasheet

Specifications



APC Smart-UPS SRT 48V 1kVA 1.5kVA Battery Pack

SRT48BP

Overview

Lead time Usually in Stock

Main

Battery type Lead-acid battery

Provided equipment Documentation CD
Installation guide

Batteries & Runtime

Number of battery free slots 0

Number of battery filled slots 0

Device mounting Stand alone battery stack

Battery voltage 48 V

Number of battery replacement quantity 2

Replacement battery [APCRBC155](#)

Physical

Colour Black

Height 43.2 cm

Width 8.5 cm

Depth 53.6 cm

Net weight 29.9 kg

Mounting mode Rack-mounted with kit

Environmental

Ambient air temperature for operation 0...40 °C

Operating altitude 0...10000 ft

Relative humidity 0...95 % non-condensing

Ambient air temperature for storage -15...45 °C

Storage altitude 0.00...15240.00 m

Storage Relative Humidity	0...95 % non-condensing
---------------------------	-------------------------

Packing Units

Unit Type of Package 1	PCE
------------------------	-----

Number of Units in Package 1	1
------------------------------	---

Package 1 Height	24.4 cm
------------------	---------

Package 1 Width	74.9 cm
-----------------	---------

Package 1 Length	59.4 cm
------------------	---------

Package 1 Weight	37 kg
------------------	-------

Offer Sustainability

Sustainable offer status	Green Premium product
--------------------------	-----------------------

REACH Regulation	REACH Declaration
------------------	-----------------------------------

EU RoHS Directive	Compliant EU RoHS Declaration
-------------------	--

Mercury free	Yes
--------------	-----

RoHS exemption information	Yes
----------------------------	---------------------

Environmental Disclosure	Product Environmental Profile
--------------------------	---

Circularity Profile	End of Life Information
---------------------	---

Optimized Energy Efficiency	Energy efficient product
-----------------------------	--------------------------

Take-back	Take-back program available
-----------	-----------------------------

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------

Recommended replacement(s)