

# Product datasheet

Specifications



## APC Smart-UPS RT Battery Pack 192V, rackmount, 4U

SRTG192XLBP2

### Overview

Lead time Usually Ships within 2 Weeks

### Main

Product or component type	Battery
number of rack unit	4U
Battery type	Lead-acid battery
Provided equipment	Installation guide Warranty card
Range of product	Smart-UPS Battery Systems

### Batteries & Runtime

Device mounting	Stand alone battery stack Rack mount
Number of battery filled slots	4
Number of battery free slots	0
Number of battery replacement quantity	2
Battery voltage	192 V
Replacement battery	<a href="#">APCRBC172</a>

### Physical

Colour	Black
Height	17.5 cm
Width	44 cm
Depth	70.0 cm
Net weight	116 kg
mounting mode	Rack-mounted
USB compatible	No

### Environmental

Ambient air temperature for operation	0...40 °C
Relative humidity	0...95 % non-condensing
Operating altitude	0...6600 ft
Storage Relative Humidity	0...95 % non-condensing

---

Storage altitude 0.0000000000...15240.0000000000 m

## Packing Units

---

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	295 mm
Package 1 Width	790 mm
Package 1 Length	590 mm
Package 1 Weight	122.4 kg

---

## Contractual warranty

---

Warranty 2 years

## Sustainability

**Green Premium™ label** is Schneider Electric's commitment to delivering products with best-in-class environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

[Learn more about Green Premium >](#)



Transparency RoHS/REACH

## Well-being performance

Toxic Heavy Metal Free

Mercury Free

Rohs Exemption Information [Yes](#)

## Certifications & Standards

**Eu Rohs Directive** [Compliant](#)  
[EU RoHS Declaration](#)

**China Rohs Regulation** [China RoHS declaration](#)  
Pro-active China RoHS declaration (out of China RoHS legal scope)

**Environmental Disclosure** [Product Environmental Profile](#)

**Weee** The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

**Circularity Profile** [End of Life Information](#)